

AUSTRALIAN  
COMMUNICATIONS  
INDUSTRY FORUM



INDUSTRY GUIDELINE  
ACIF G624:2005  
NETWORK INTERFACE VOLTAGE LEVELS

**ACIF G624:2005 Network interface voltage levels**  
**First published as ACIF G624:2005**

**Disclaimers**

1. Notwithstanding anything contained in this Guideline:
  - (a) ACIF disclaims responsibility (including where ACIF or any of its officers, employees, agents or contractors has been negligent) for any direct or indirect loss, damage, claim, or liability any person may incur as a result of any:
    - (i) reliance on or compliance with this Guideline;
    - (ii) inaccuracy or inappropriateness of this Guideline; or
    - (iii) inconsistency of this Guideline with any law; and
  - (b) ACIF disclaims responsibility (including where ACIF or any of its officers, employees, agents or contractors has been negligent) for ensuring compliance by any person with this Guideline.
2. The above disclaimers will not apply to the extent they are inconsistent with any relevant legislation.

**Copyright**

© Australian Communications Industry Forum Limited 2005

This document is copyright and must not be used except as permitted below or under the *Copyright Act 1968*. You may reproduce and publish this document in whole or in part for your or your organisation's own personal or internal compliance, educational or non-commercial purposes. You must not alter or amend this document in any way. You must not reproduce or publish this document for commercial gain without the prior written consent of ACIF. Organisations wishing to reproduce or publish this document for commercial gain (i.e. for distribution to subscribers to an information service) may apply to subscribe to the *ACIF Publications Subscription Service* by contacting the ACIF Business Manager at [acif@acif.org.au](mailto:acif@acif.org.au). If you publish any part of this document for any purpose, you must also publish this copyright notice as part of that publication.

---

<b>TABLE OF CONTENTS</b>		
<b>1</b>	<b>GENERAL</b>	<b>2</b>
	1.1 Scope	2
	1.2 Objectives	2
<b>2</b>	<b>ACRONYMS, DEFINITIONS AND INTERPRETATIONS</b>	<b>3</b>
	2.1 Acronyms and abbreviations	3
	2.2 Definitions	4
<b>3</b>	<b>NETWORK INTERFACE VOLTAGE LEVELS</b>	<b>5</b>
<b>4</b>	<b>REFERENCES</b>	<b>8</b>
	<b>PARTICIPANTS</b>	<b>9</b>

---

# 1 GENERAL

## 1.1 Scope

This Guideline provides guidance for designers of CE and test laboratories, indicating the minimum voltage levels that should be supported for each category of CE in the TLN for which a safety Standard is required.

*NOTE: IEC TR 62102 provides further useful information about the classification of network interfaces, including phenomena affecting the safety of interface ports.*

## 1.2 Objectives

This Guideline was developed with the following objectives:

- (a) To provide information to designers of CE about the minimum voltage levels expected to be encountered by CE in Australia.
- (b) To provide information to test laboratories about the voltage levels to which CE should be tested under each category in the TLN.

## 2 ACRONYMS, DEFINITIONS AND INTERPRETATIONS

### 2.1 Acronyms and abbreviations

For the purposes of the Guideline, the following acronyms apply:

<b>3G</b>	Third Generation Mobile Communications
<b>AC</b>	Alternating Current
<b>ACMA</b>	Australian Communications and Media Authority
<b>ACIF</b>	Australian Communications Industry Forum
<b>ADSL</b>	Asymmetric Digital Subscriber Line
<b>AMPS</b>	Advanced Mobile Phone System
<b>ASA</b>	Air Services Australia
<b>AS/NZS</b>	Australian Standard/New Zealand Standard
<b>BRA</b>	Basic Rate Access
<b>CAS</b>	Channel Associated Signalling
<b>CDMA</b>	Code-Division Multiple Access
<b>CE</b>	Customer Equipment
<b>CECRP</b>	Customer Equipment and Cable Reference Panel
<b>CT2</b>	Cordless Telephone Second Generation
<b>DC</b>	Direct Current
<b>DECT</b>	Digital Enhanced Cordless Telecommunications
<b>ETSI</b>	European Telecommunications Standards Institute
<b>GSM</b>	Global System for Mobile Communications
<b>ISDN</b>	Integrated Services Digital Network
<b>LIU</b>	Line Isolation Unit
<b>LMB</b>	Large Mega bit Bearer
<b>MOH</b>	Music on Hold
<b>PABX</b>	Private Automatic Branch Exchange
<b>PHS</b>	Personal Handyphone System
<b>PMTS</b>	Public Mobile Telephone Service
<b>POTS</b>	Plain Old Telephone Service
<b>PRA</b>	Primary Rate Access
<b>SDSL</b>	Symmetric Digital Subscriber Line
<b>SELV</b>	Safety Extra Low Voltage
<b>SHDSL</b>	Symmetrical High-speed Digital Subscriber Loop
<b>TLN</b>	Telecommunications Labelling Notice
<b>TNV</b>	Telecommunications Network Voltage
<b>WC</b>	Working Committee

## 2.2 Definitions

### 2.2.1 Voltage Ranges of SELV circuits and TNV circuits

The voltage relationships between SELV circuits and TNV circuits are shown in the following table:

Overvoltage from telecommunication network possible?	Normal operating voltages	
	Within SELV circuit limits	Exceeding SELV circuit limits but within TNV circuit limits
Yes	TNV-1 circuit	TNV-3 circuit
No	SELV circuit	TNV-2 circuit

### 2.2.2 Over-voltage Conditions: Lightning

Lightning may occur naturally at any location and the maximum open circuit voltage, between the TNV conductors and the main earth bar, could be up to 7 kV peak. This is in accordance with AS 4262.1, i.e. protection is installed if the voltage is likely to exceed 7 kV and when protection is installed the voltage is limited to 7 kV.

### 2.2.3 Over-voltage Conditions: Power Induction/EPR

In known EPR Zones, the service is isolated to the maximum expected 50 Hz voltage in accordance with the Earth Potential Rise Code.

In other areas, the likely maximum open circuit voltage, is in accordance with HB 101-1997, and could be:

- (a) 2.1 kV peak 50 Hz for 350 ms (1.5 kV r.m.s. as specified in HB 101-1997).
- (b) 1.4 kV peak 50 Hz for 500 ms (1.0 kV r.m.s. as specified in HB 101-1997).
- (c) 610 V peak 50 Hz for 2 s (430 V r.m.s. as specified in HB 101-1997).
- (d) 84 V peak 50 Hz continuous (60 V r.m.s. as specified in HB 101-1997).

### 3 NETWORK INTERFACE VOLTAGE LEVELS

The following table lists the 'A', 'B' and 'C' categories from the ACMA Telecommunications Labelling (Customer Equipment and Customer Cabling) Notice for which safety testing is required, and the corresponding recommended voltage levels.

Where different Carriage Service Providers support an interface at different voltage levels, the 'worst-case' for the relevant category is identified. CE which is designed and tested to this, the most severe voltage requirement, will therefore be supported by all Carriage Service Providers. Where a device is tested to a less severe level, for connection to a specified carrier, it is suggested that the equipment bear a label stating the voltage level to which it can be connected, and that the test laboratory note that the level supported is lower than the one identified herein.

Designers of SELV-rated multiplexers should be aware that cables may run outside the building in which it is located, in which case TNV levels may be encountered. In such cases, care should be taken with link-to-link isolation, and consideration given to the provision of suitable warning notices on the CE.

While wireless equipment doesn't have a conductive network interface, the equipment is subject to the requirements of AS/NZS 60950.

TLN Category	TLN Category Item	Voltage Level	Examples and notes
A1	CE designed to connect to PSTN – Analogue for voice	TNV-3	Analogue PABX trunk circuits, telephones
A2	CE Designed to connect to PSTN – Analogue for data	TNV-3	Analogue PABX trunk circuits, modems
A3	CE designed to connect to PSTN – digital channel associated signalling (CAS) for voice operation	SELV	Some non-Telstra CAS services
A4	CE designed to connect to PSTN – digital CAS interface for data only	SELV	Some non-Telstra CAS services
A7	CE designed to connect to ISDN – TS014 PRA incorporating voice	SELV	Some non-Telstra ISDN services
A8	CE designed to connect to ISDN – TS014 PRA for data	SELV	Some non-Telstra ISDN services
A9	CE designed to connect to ISDN – BRA incorporating voice	SELV	Telstra's 'on-Ramp-2' service
A10	CE designed to connect to ISDN – BRA for data	SELV	Telstra's 'on-Ramp-2' service

<b>TLN Category</b>	<b>TLN Category Item</b>	<b>Voltage Level</b>	<b>Examples and notes</b>
A11	CE designed to connect to ISDN – ETSI PRA incorporating voice	SELV	Telstra's 'on-Ramp-30' service
A12	CE designed to connect to ISDN – ETSI PRA for data	SELV	Telstra's 'on-Ramp-30' service
A14	CE designed to connect to dedicated digital – LMB (2.048 Mbit/s interface)	TNV-1	Telstra's 'Megalink' services. Note: may be subject to surges.
	CE designed to connect to dedicated digital – LMB (over 2.048 Mbit/s)	SELV	Telstra's 'Megalink' services
A18	Dedicated video CE – without TS024 broadcaster LIU	SELV	Analogue video service
A19	Broadcaster LIU	SELV	Analogue video service
A20	ASA LIU	TNV-3	
A21	CE designed to connect to telex	TNV-3	
A23	Mobile equipment – AMPS	SELV	
A24	Mobile equipment – GSM	SELV	
A25	Mobilesat terminal	SELV	
A26	Cordless telecommunications – CT2	SELV	Cordless handsets
A27	Cordless telecommunications – PHS	SELV	Cordless handsets
A28	Cordless telecommunications – DECT	SELV	Cordless handsets
A39	Mobile equipment – CDMA	SELV	
A49	CE designed for connection to a non-switched voiceband only service	TNV-3	Voice-grade private lines with ring signal, e.g. outdoor extensions
A50	CE designed for connection to a metallic local loop (including broadband, DC power feeding, DC signalling, low frequency AC, voiceband or signalling up to 20 kHz)	TNV-3	xDSL equipment  Note: Test laboratories should determine, at time of testing, any special requirements to accommodate remote power-feed systems.
A51	Disability CE	TNV-3	



<b>TLN Category</b>	<b>TLN Category Item</b>	<b>Voltage Level</b>	<b>Examples and notes</b>
A52	Surge protective devices	TNV-3	
A53	CE used in the supply of a PMTS	SELV	'3G' mobile services
B29	System integral terminal that is part of a system	System dependant	Test laboratories should determine, at time of testing, the appropriate voltage level for the device, taking into account the characteristics of the interface to which it is to be connected.
B30	Wireless equipment (CT2, PHS, DECT), including proprietary wireless, that is part of a system	SELV	
B31	Interface for connection of extensions	TNV-2	Indoor extension interface
		TNV-3	Outdoor extension interface
C33	System integral terminal supplied separately	System dependant	Test laboratories should determine, at time of testing, the appropriate voltage level for the device, taking into account the characteristics of the interface to which it is to be connected.
C34	Wireless equipment (CT2, PHS, DECT), including proprietary wireless	SELV	
C35	Digital isolator	System dependant	
C36	Headset or amplifier	TNV-3	
C38	Music-on-hold LIU	System dependant	The test laboratory must determine the appropriate voltage level to protect the CE and network from unknown voltages occurring in the MOH source

## 4 REFERENCES

<b>Publication</b>	<b>Title</b>
<b>Australian Standards</b>	
AS 4262.1-1995	Telecommunication Overvoltages – Protection of Persons
AS/NZS 60950:2000	Safety of information technology equipment, including Amendment 1
AS/NZS 60950.1:2003	Information technology equipment - Safety - Part 1: General requirements
HB 101-1997 (CJC 5)	Coordination of power and telecommunications - Low Frequency Induction (LFI): Code of practice for the mitigation of hazardous voltages induced into telecommunications lines
<b>Other references</b>	
ACMA TLN	Telecommunications Labelling (Customer Equipment and Customer Cabling) Notice 2001
IEC TR 62102	Electrical Safety – Classification of interfaces for equipment to be connected to information and communications technology networks
Earth Potential Rise Code (Note)	Code of Practice for the Protection of Personnel and Equipment Against Earth Potential Rises Caused by High Voltage Power System Faults

*NOTE: The Earth Potential Rise Code (EPR Code), Issue 1, 1984 was published jointly by the Australian Telecommunications Commission (ATC) (now Telstra Corporation) and ESAA. This publication is available from Energy Supply Association of Australia Ltd, GPO Box 1823Q, Melbourne, Victoria 3001.*

## **PARTICIPANTS**

The Working Committee that developed this Guideline consisted of the following organisations and their representatives:

<b>Organisation</b>	<b>Membership</b>	<b>Member</b>
ACMA	Non voting	Peter Joynson
Austest Laboratories	Voting	John Wang
Cisco Systems	Voting	Kim Yan
Comtest Laboratories	Voting	Peter Arms
Consumers' Telecommunications Network	Voting	Sarah Wilson
IBM (Australian Information Industry Association)	Voting	Paul Robinson
NEC	Voting	Ian Faichney
Optus	Voting	Aaron Bui
Siemens	Voting	Bob Davis
Stanimore (Australian Information Industry Association)	Voting	Kevin Richardson
Telstra	Voting	Phil Day
Thomson Telecom Australia	Voting	Laurie Collier

This Working Committee was chaired by Merv Sewell of Telstra until June 2004, then Bob Davis. Mike Johns of ACIF provided project management support

The policy objective of the greatest practicable use of industry self-regulation without imposing undue financial and administrative burdens on industry is central to the regulatory scheme of the *Telecommunications Act 1997*.

ACIF was established to implement the policy of industry self-regulation. It is a company limited by guarantee and is a not-for-profit membership-based organisation. Its membership comprises carriers/carriage service providers, business and residential consumer groups, industry associations and individual companies.

ACIF's mission is to develop collaborative industry outcomes that foster the effective and safe operation of competitive networks, the provision of innovative services and the protection of consumer interests. In the development of Industry Codes and Technical Standards as part of its mission, ACIF's processes are based upon its principles of openness, transparency, consensus, representation and consultation. Procedures have been designed to ensure that all sectors of Australian society are reasonably able to influence the development of Standards and Codes. Representative participation in the work of developing a Code or Standard is encouraged from relevant and interested parties. All draft Codes and Standards are also released for public comment prior to publication to ensure outputs reflect the needs and concerns of all stakeholders.



Published by:  
**THE AUSTRALIAN  
COMMUNICATIONS  
INDUSTRY FORUM LTD**

Level 9  
32 Walker Street  
North Sydney  
NSW 2060 Australia

Correspondence:  
PO Box 444  
Milsons Point  
NSW 1565

T 61 2 9959 9111  
F 61 2 9954 6136  
TTY 61 2 9923 1911  
E [acif@acif.org.au](mailto:acif@acif.org.au)  
[www.acif.org.au](http://www.acif.org.au)  
ABN 56 078 026 507

Care should be taken to ensure that material used is from the current version of the Standard or Industry Code and that it is updated whenever the Standard or Code is amended or revised. The number and date of the Standard or Code should therefore be clearly identified. If in doubt please contact ACIF.